

Model Number Doc No PERFORMANCE SPECIFICATION 1060V4 PS1060V4 Force Sensors, IEPE REV A, ECN 12920, 08/23/16



- DYNAMIC FORCE SENSOR
- VOLTAGE MODE

		ENGLISH		SI	
PHYSICAL			_		
Weight, Max.		16.10	oz	460	grams
Connector	Туре	Coaxial		Coaxial	
	Thread	10-32		10-32	
Housing	Material	Stainless steel		Stainless steel	
	Isolation	Case grounded		Case grounded	
Sensing Element	Material	Quartz		Quartz	
	Mode	Compression		Compression	
PERFORMANCE		0.5	7	0.44	7
Sensitivity, +/-10% Compression Range		0.5	mV/Lb	0.11	mV/N
Maximum Compression , +/-5%		10000	Lbs.Force	44480	N
Tension Range		40000	Lbs.Force	177920	N
•		1000	Lbs.Force	4448	N
Maximum Tension [1], +/-5%		1000	Lbs.Force	4448	N
Resolution		.14	Lb. RMS	0.62272	N RMS
Linearity [2]		±1	% Full Scale	±1	% Full Scale
Mounted Resonance (Unloaded)		≥ 75	kHz	≥ 75	kHz
Stiffness		50	Lb/μin	8.66	kN/μm
ENVIRONMENTAL					
Coefficient Of Thermal Sensitivity		0.03	%/°F	0.05	%/°C
Operating Temperature		-100 to +250	°F	-73 to +121	°C
Maximum Vibration		±3000	g's,Peak	±29400	m/s^2 Peak
Maximum Shock		5,000	g's,Peak	49,000	m/s^2 Peak
Environmental Seal		Ероху		Ероху	
ELECTRICAL					
Supply Current [3]		2 to 20	mA	2 to 20	mA
Compliance Voltage		18 to 30	VDC	18 to 30	VDC
Discharge Time Constant, Min.		2000	Seconds	2000	Seconds
F.S. Output Voltage		5	Volts	5	Volts
Output Impedance		100	Ω	100	0

This family also includes:								
Model	Sensitivity (mV/Lb)	Range (LbsF) Compressive, Tensile	Max Force (LbsF) Compressive, Tensile	Discharge Time Constant (Sec)				
1060V1	10	500, 500	10000, 1000	150				
1060V2	5	1000, 1000	20000, 1000	300				
1060V3	1	5000, 1000	30000, 1000	1500				
1060V5	0.2	25000, 1000	50000, 1000	2000				
1060V6	0.1	50000, 1000	60000, 1000	2000				


Refer to the performance specifications of the products in this family for detailed description


Supplied Accessories:

- 1) Accredited Calibration Certificate (ISO 17025)
- 2) MOD 6232 MOUNTING STUD

Notes:

- [1] Absolute maximum tension. Do not exceed in any case!
- [2] Percent of full scale or any lesser range, zero based best-fit sraight line method.
- [3] Power these instruments only with constant current type power units. Do not connect to a source of voltage without current limiting. This will destroy the integral IC amplifier.







21592 Marilla Street, Chatsworth, California 91311 Phone: 818.700.7818 Fax:818.700.7880 www.dytran.com For permission to reprint this content, please contact info@dytran.com