

Model Number Doc No PERFORMANCE SPECIFICATION 1060V3 PS1060V3 Force Sensors, IEPE REV A, ECN 12920, 08/23/16



- DYNAMIC FORCE SENSOR

VOLTAGE MODE EXCELLENT LINEARITY						
		ENGLISH		SI		
PHYSICAL			- -		_	
Weight, Max.		16.10	oz	460	grams	
Connector	Type	Coaxial		Coaxial		
	Thread	10-32		10-32		
Housing	Material	Stainless steel		Stainless steel		
	Isolation	Case grounded		Case grounded		
Sensing Element	Material	Quartz		Quartz		
	Mode	Compression		Compression		
PERFORMANCE						
Sensitivity, +/-10%		1	mV/Lb	0.22	mV/N	
Compression Range		5000	Lbs.Force	22240	N	
Maximum Compression , +/-5%		30000	Lbs.Force	133440	N	
Tension Range		1000	Lbs.Force	4448	N	
Maximum Tension [1], +/-5%		1000	Lbs.Force	4448	N	
Resolution		.07	Lb. RMS	0.31136	N RMS	
Linearity [2]		± 1	% Full Scale	± 1	% Full Scale	
Mounted Resonance (Unloaded)		≥ 75	kHz	≥ 75	kHz	
Stiffness		50	Lb/µin	8.66	kN/μm	
ENVIRONMENTAL						
Coefficient Of Thermal Sensitivity		0.03	%/°F	0.05	%/°C	
Operating Temperature		-100 to +250	°F	-73 to +121	°C	
Maximum Vibration		±3000	g's,Peak	±29400	m/s^2 Peak	
Maximum Shock		5,000	g's,Peak	49.000	m/s^2 Peak	
Environmental Seal		Ероху]	Ероху		
ELECTRICAL						
Supply Current [3]		2 to 20	mA.	2 to 20	mA.	
Compliance Voltage		18 to 30	VDC	18 to 30	VDC	
Discharge Time Constant, Min.		1500	Seconds	1500	Seconds	
F.S. Output Voltage		5	Volts	5	Volts	
Output Impedance		100	Ω	100	Ω	

This family also includes:								
Model	Sensitivity (mV/Lb)	Range (LbsF) Compressive, Tensile	Max Force (LbsF) Compressive, Tensile	Discharge Time Constant (Sec)				
1060V1	10	500, 500	10000, 1000	150				
1060V2	5	1000, 1000	20000, 1000	300				
1060V4	0.5	10000, 1000	40000, 1000	2000				
1060V5	0.2	25000, 1000	50000, 1000	2000				
1060V6	0.1	50000, 1000	60000, 1000	2000				


Refer to the performance specifications of the products in this family for detailed description


Supplied Accessories:

- 1) Accredited Calibration Certificate (ISO 17025)
- 2) MOD 6232 MOUNTING STUD

Notes:

- [1] Absolute maximum tension. Do not exceed in any case!
- [2] Percent of full scale or any lesser range, zero based best-fit sraight line method.
- [3] Power these instruments only with constant current type power units. Do not connect to a source of voltage without current limiting. This will destroy the integral IC amplifier.





Units on the line drawing are in inches, units in brackets are in millimeters. Refer to 127-1060V for more information.



21592 Marilla Street, Chatsworth, California 91311 Phone: 818.700.7818 Fax:818.700.7880 www.dytran.com For permission to reprint this content, please contact info@dytran.com