Actual

 ϵ

Product Size Shown

mini-MIL Must Use J2X Series Connectors


Product Features-

Very High g Side Exit Accelerometer for High Frequency Applications

Helps to Detect Gearbox Defects and Other High Frequency Faults

- 1,0 25000 Hz (60 1,500,000 CPM) Frequency Response
- 10 mV/g, ±5% Sensitivity
- 34 kHz Resonant Frequency









Specifications	Standard	Metric		
Part Number	AC220	M/AC220		
Sensitivity (±5%)	10 mV/g			
Frequency Response (±3dB) Frequency Response (±10%) Frequency Response (±5%)	60-1,500,000 CPM 90-420,000 CPM 180-180,000 CPM	1,0-25000 Hz 1,5-7000 Hz 3,0-3000 Hz		
Dynamic Range	± 500 g, peak			
Electrical				
Settling Time	<2 Seconds			
Voltage Source (IEPE)	18-30 VDC			
Constant Current Excitation	2-10 n	2-10 mA		
Spectral Noise @ 10 Hz	100 μg/√Hz			
Spectral Noise @ 100 Hz	19 μg/√Hz			
Spectral Noise @ 1000 Hz	5 μg/√Hz			
Output Impedance	<100 ohm			
Bias Output Voltage	10-14 V	/DC		
Case Isolation	>10 ⁸ ohm			

Specifications	Standard	Metric	
<u>Environmental</u>			
Temperature Range	-58 to 250°F	-50 to 121°C	
Maximum Shock Protection	5,000 g, peak		
Electromagnetic Sensitivity	CE		
Sealing	IP68		
Submersible Depth (AC220-2D/3D)	200 ft.	60 m	
<u>Physical</u>			
Sensing Element	PZT Ceramic		
Sensing Structure	Shear Mode		
Weight	0.7 oz	20 grams	
Case Material	316L Stainless Steel		
Mounting	1/4-28		
Connector (non-integral)	2 Pin mini-MIL		
Resonant Frequency	2,040,000 CPM	34000 Hz	
Mounting Torque	2 to 5 ft. lbs.	2,7 to 6,8 Nm	
Mounting Hardware	1/4-28 Stud	M6x1 Adapter Stud	
Calibration Certificate	C	A10	

Ordering Information

	•			
Standard	AC220-1D (1/4-28 Stud) Stock Product	AC220-2D - / [1/4-28 Stud] Build (length in feet) (termination)	AC220-3D - / (1/4-28 Stud) (maximum armor length 100 ft.)	(cable length in feet) - (termination)
Metric	M/AC220-1D (M6x1 Adapter Stud) Stock Product	M/AC220-2D - / -	M/AC220-3D - / / / / / / / / / / / / / / / / / /	(cable length in feet) (termination) / M / (cable length in meters) (termination)

Cable Termination Options: E F F L

