## LP302-M12 Series

Loop Power Sensor, Acceleration, 4-20 mA Output, Top Exit M12 Connector




Œ

## Product Features Continuously Monitor & Protect Important Machinery

- 4-20 mA Current Proportional to Vibration
- Transmit Signals Over Long Distances with No Signal Loss
- Customize Your Settings to Focus on the Most Important Frequencies

Actual Product Size Shown



Г

Specifications	Standard	Metric	Specifications
Output, 4-20 mA	See Selection Guide		Physical
Measurement Range		Sensing Element	
<u>Tolerances</u>			Sensing Structure
4 mA	(± 5%) Weight		Weight
20 mA	(± 1	0%)	Case Material
Electrical			Mounting
Settling Time (Turn on Time) @ Room Temp (68° F/20° C)	<30 Seconds		Connector (LP302-M12E)
Power Requirement (Loop Powered)	15-30 VDC		Mechanical
Voltage Source	15 50	, vbc	Mounting Torque
Electrical Case Isolation	>10 <sup>8</sup> ohm		Supplied Accessories
<u>Environmental</u>			Mounting Hardware
Temperature Range	-40 to 212°F	-40 to 100°C	Calibration Certificate
Electromagnetic Sensitivity	C	E	
Sealing	IP68		

Specifications	Standard	Metric				
Physical						
Sensing Element	PZT Ceramic					
Sensing Structure	Shea	ar Mode				
Weight	2.9 oz	82 grams				
Case Material	316L Sta	ainless Steel				
Mounting	1/4-28					
Connector (LP302-M12E)	4 P	in M12				
Mechanical						
Mounting Torque	2 to 5 ft. lbs.	2,7 to 6,8 Nm				
Supplied Accessories						
Mounting Hardware	1/4-28 Stud	M6x1 Adapter Stud				
Calibration Certificate	Current Ou	itput @ 100 Hz				

## **Ordering Information**

	P302 -		-	Μ	1	2	Ε
Stud Type	Measurement Range	Range Type	Frequency Range +/- 3dB	Style			
M = M6x1	0 = 0-1 g	R = RMS	1 = 600-60,000 CPM (10-1000 Hz)	M12E =	4 Pin	M12	
(blank for 1/4-28)	2 = 0-2 g	P = Peak	2 = 180-150,000 CPM (3-2500 Hz)				
(DIANK IOF 1/4-28)	5 = 0-5 g		3 = 180-60,000 CPM (3-1000 Hz)				
	10 = 0-10 g		4 = 180-300,000 CPM (3-5000 Hz)				
	20 = 0-20 g		5 = 180-600,000 CPM (3-10000 Hz)				



Lifetime Warranty on Materials & Workmanship Page 425 • 800-999-5290